

# Solution 2000 / 3000 Control Panel

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ 8/16 Fully Programmable Zones
- ▶ 41 Codes – 1 Installers, 20 User Codes, 20 RF Keyfobs
- ▶ 16 Wireless Devices (on Solution 3000)
- ▶ Partitionable into 2 Separate Areas
- ▶ STAY / AWAY Arming Options

The Solution 2000 and Solution 3000 are new generation alarm control panels for the Australian & New Zealand residential & commercial markets.

## System overview

Supporting up to 8 fully programmable zones on the Solution 2000 and 16 fully programmable zones on the Solution 3000, this range of intrusion panels is suitable for any home, and even some commercial premises.

With support for up to four keypads on both panels and the ability to be split into two separate partitions on the Solution 3000, you have the flexibility of one security system that can act as two.

## Functions

### User Interfaces

The Solution 2000 and 3000 control panels have the variety of keypad options, including LCD Icon, LCD Alphanumeric, and various touchscreen options that are simple to use.

### Wireless

The Solution 2000 supports the WE800EV2 wireless receiver for wireless keyfob control, while the Solution

3000 supports both the WE800EV2 and the option to integrate with the Bosch RADION range of wireless transmitters.

### Communication

Solution 2000 and 3000 also have available a range of communications extension modules that integrate directly with the panel and provide options such as mobile communications via the GSM & GPRS networks, along with IP reporting through the internet. The IP module includes CSV-IP communications technology and makes the panels fully NBN-ready with the majority of monitoring centres in Australia & New Zealand able to handle the IP communications from the Solution 2000 and 3000.

### Remote Security Control (RSC) app

The Solution 2000 and 3000 control panels support the Bosch Remote Security Control (RSC) app, enabling convenient system operation from an iPhone, iPad or iPod Touch, including arming / disarming of the system and control of connected devices, such as lighting and A/C.

### Certifications and approvals

Australia	RCM
New Zealand	Tele-permit
Europe	PCE – EN61000-3:2007/ A1:2011 EN501030-4:2011AS/CA S002:2010

### Technical specifications

#### Power Requirements

Primary	250 VAC / 18 VAC at 1.3A supplied by TF008 Plug Pack
Secondary	12 VDC, 6.5Ah from rechargeable sealed lead/acid battery

#### Communications

Communications	CID, SIA, Email*, Domestic Dialing, CSV-IP *Requires B426 IP Communications Module or B450 Universal Communications Module
----------------	---

#### Environmental Considerations

Temperature	0° to +45°C
Relative Humidity	10% to 95% non-condensing

#### Enclosure

Dimensions (H x W x D) (packed in carton)	306 x 262 x 84mm
Weight	2.5kg
Warranty	3 years

### Ordering information

**ICP-SOL2-P Solution 2000 Control Panel**  
Order number **ICP-SOL2-P**

**ICP-SOL3-P Solution 3000 Control Panel**  
Order number **ICP-SOL3-P**

#### Accessories

**IUI-SOL-TEXT LCD Text Keypad**  
Order number **IUI-SOL-TEXT**

**IUI-SOL-ICON LCD Keypad**  
Order number **IUI-SOL-ICON**

**IUI-SOL-TS4 4" Touchscreen Keypad**  
Order number **IUI-SOL-TS4**

**IUI-SOL-TS7 7" Premium Touchscreen Keypad**  
Order number **IUI-SOL-TS7**

**B308 Octo-Output Expansion Module**  
Order number **B308**

### B426 IP Communications Module

Order number **B426**

บริษัท ที.เอส.อาร์. - เทคโนโลยี ซีสเต็มส์ จำกัด  
โทร 02-528-0383 ถึง 7 สายด่วน 08-1824-6471  
Email : sales@tsr.co.th  
Line ID : @tsrtelecom  
Website : tsr.co.th

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
203 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com